

Procédure de remise à zéro du commutateur HPE

Après avoir effectué les différents raccordements (électrique et donnée). Vous devez obtenir la console suivante :

[illegible]

En appuyant deux fois sur la touche « Entrée » vous arrivez sur l'interface utilisateur :

```
Press ENTER to get started.
<HPE>
#Jan 1 05:58:39:475 2010 HPE SHELL/4/LOGIN:
Trap 1.3.6.1.4.1.25506.2.2.1.1.3.0.1: login from Console
%Jan 1 05:58:39:606 2010 HPE SHELL/5/SHELL_LOGIN: Console logged in from aux0.
<HPE>
```

Passer en mode configuration

```
<HPE>system-view
System View: return to User View with Ctrl+Z.
[HPE]
```

Désactiver le mot de passe de récupération

```
[HPE]undo password-recovery enable
The command will disable the password recovery function. Continue? [Y/N]:Y
[HPE]
```

Quitter l'interface de configuration

```
[HPE]quit  
<HPE>
```

Sauvegarder les paramètres

```
<HPE>save  
The current configuration will be written to the device. Are you sure? [Y/N]:Y  
Please input the file name(*.cfg)[flash:/config.cfg]  
(To leave the existing filename unchanged, press the enter key):  
flash:/config.cfg exists, overwrite? [Y/N]:Y  
Validating file, Please wait....  
The current configuration is saved to the active main board successfully.  
Configuration is saved to device successfully.  
<HPE>
```

Redémarrer le switch

```
<HPE>reboot  
Start to check configuration with next startup configuration file, please wait.....DONE!  
This command will reboot the device. Continue? [Y/N]:Y  
#Jan 1 06:04:43:434 2010 HPE DEVM/1/REBOOT:  
Reboot device by command.
```

Accéder au Boot menu

Lorsque vous y êtes invité effectuer la combinaison de touche clavier « CTRL+B » pour accéder au BOOT MENU.

```
%Jan 1 06:04:43:524 2010 HPE DEVM/5/SYSTEM_REBOOT: System is rebooting now.  
Starting.....  
Press Ctrl+D to access BASIC BOOT MENU  
  
*****  
*                               *  
*       HPE 3600-48 v2 SI Switch B00TR0M, Version 131       *  
*                               *  
*****  
Copyright (c) 2010-2015 Hewlett Packard Enterprise Development LP  
  
Creation Date       : Dec  8 2015, 14:30:43  
CPU Clock Speed    : 400MHz  
Memory Size        : 256MB  
Flash Size         : 128MB  
CPLD Version       : 001  
PCB Version        : Ver.B  
Mac Address        : 943fc2a7bfae  
  
Press Ctrl-B to enter Extended Boot menu...0
```

Le BOOT MENU apparaît :

```
BOOT MENU  
1. Download application file to flash  
2. Select application file to boot  
3. Display all files in flash  
4. Delete file from flash  
5. Restore to factory default configuration  
6. Enter BootRom upgrade menu  
7. Skip current system configuration  
8. Reserved  
9. Set switch startup mode  
0. Reboot  
Ctrl+F: Format File System  
Ctrl+P: Skip Super Password  
Ctrl+R: Download application to SDRAM and Run  
Ctrl+Z: Access EXTEND-ASSISTANT MENU  
Ctrl+C: Display Copyright  
Enter your choice(0-9):
```

Restaurer la configuration usine

```
BOOT MENU
1. Download application file to flash
2. Select application file to boot
3. Display all files in flash
4. Delete file from flash
5. Restore to factory default configuration
6. Enter BootRom upgrade menu
7. Skip current system configuration
8. Reserved
9. Set switch startup mode
0. Reboot
Ctrl+F: Format File System
Ctrl+P: Skip Super Password
Ctrl+R: Download application to SDRAM and Run
Ctrl+Z: Access EXTEND-ASSISTANT MENU
Ctrl+C: Display Copyright
Enter your choice(0-9): 5
```

```
Because the password recovery capability is disabled, this operation can cause
the configuration files to be deleted, and the system will start up with
factory defaults. Are you sure to continue?[Y/N]Y
Setting...Done.
```

Redémarrer le switch

```
BOOT MENU
1. Download application file to flash
2. Select application file to boot
3. Display all files in flash
4. Delete file from flash
5. Restore to factory default configuration
6. Enter BootRom upgrade menu
7. Skip current system configuration
8. Reserved
9. Set switch startup mode
0. Reboot
Ctrl+F: Format File System
Ctrl+P: Skip Super Password
Ctrl+R: Download application to SDRAM and Run
Ctrl+Z: Access EXTEND-ASSISTANT MENU
Ctrl+C: Display Copyright
Enter your choice(0-9): 0
Starting.....
Press Ctrl+D to access BASIC BOOT MENU
```

Le switch a été remis aux paramètres par défaut d'usine
